Sms C		
sn	s	Command
1	Add number	*100#phonenumber#
2	delete number	*101#phonenumber#
3	add email	*110#email#
4	delet email	*111#email#
5	send via	*120#sendvia#
6	receive mode	*130#sendto#
7	Send Mode	*140#sendmode#
8	work mode	*200#mode#
9	set PIR status	*202#option#
10	retrieve picture	*500#
11	status	*160#
12	sms off	*170#

Control Command List

Samples	Date
add phone mnuber88888888 *100#88888888#	Feb 25 2014
delete the specified phone number	Feb 25 2014
	Feb 25 2014
	Feb 25 2014
*120#0# //mms *120#1# //internet	Feb 25 2014
*130#0# //photo only *130#1# //email only *130#2# //both	Feb 25 2014
*140#0# //Instant *140#1# //Daily Report *140#2# //OFF	Apr 11 2014
*200#0# //phote *200#1# //video	Feb 25 2014
*202#0# //set to HIGH *202#1# //set to NORMAL *202#2# //set to LOW *202#3# //set to OFF	Apr 24 2014
	Feb 25 2014
signal/battery/SD card statues	Jun 24 2014
	Jun 24 2014

Remarks
support 4 receive phone numbers only
if send via changed to Internet, send to will be changed to email only
if camera mode is movie, execute fail
For exmple:Signal:4,Battery:5,SD total:03760M,remain:00005M
SMS control disabled